

► TASK Perform charging system output test; determine necessary action.

MLR
6D1

AST
6D1

MAST
6D1

Time off _____

Time on _____

Total time _____

CDX Tasksheet Number: C315

1. Research "performing a charging system output test" in the appropriate service information for the vehicle you are working on. **What is the specified charging system output?** _____ **amps at** _____ **volts at** _____ **rpm**
2. Install the fender covers, exhaust hose(s), and wheel chocks, and set the parking brake.
3. Connect the charging system tester as outlined in the appropriate service information.
 - a. Heavy red lead to the battery positive terminal
 - b. Heavy black lead to the battery negative terminal
 - c. Green/Black amps clamp around alternator output wire (facing the correct direction)
4. Have your supervisor/instructor verify your test procedure and connections. **Supervisor's/instructor's initials:** _____
5. Conduct the charging system output test. **List the measured results at the maximum output:** _____ **amps at** _____ **volts at** _____ **engine rpm**
6. Compare your results to the manufacturer's specifications. **List your observations:**
7. **Determine any necessary action(s):**
8. Have your supervisor/instructor verify satisfactory completion of this procedure, any observations found, and any necessary action(s) recommended.

Performance Rating

CDX Tasksheet Number: C315

0

1

2

3

4

Supervisor/instructor signature _____ Date _____

