

8. Measure the voltage drop from the bulb ground to the battery negative post.

- a. List the voltage drop: _____ volts
- b. Is this within specifications? Yes: _____ No: _____
- c. Determine any necessary action(s): _____

9. Install exhaust hose(s) and wheel chocks, and set the parking brake. Start the vehicle.

10. Measure the charging system voltage at the battery, with the engine running at 1500 rpm: _____ volts

- a. Is this within specification? Yes: _____ No: _____

NOTE If the battery voltage is too high, you will need to perform charging system checks to determine the cause of the overcharge.

11. List your observations: _____

12. Determine any necessary action(s): _____

13. Have your supervisor/instructor verify satisfactory completion of this procedure, any observations found, and any necessary action(s) recommended.

Performance Rating

CDX Tasksheet Number: C320

0

1

2

3

4

Supervisor/instructor signature _____ Date _____